

ACTISYS FIR - USB ADAPTER

ACTISYS IR2002UL, an advanced wireless Fast Infrared USB adapter

- Simply attaches to a PC's USB (Universal Serial Bus) port and gives user the wireless data transfer for data logging, synchronization, file transfer, backup, printing or network access.
- Supports FIR (4Mbps), MIR 1.152Mbps, and all SIR speeds (9.6K, 19.2K, 38.4K, 57.6K and 115.2Kbps).
- Compatible with any IrDA[®]-capable notebook PC, PDA, modem, printers, instruments, data terminals, digital camera, image capture device and others.
- Takes advantage of the true plug-and-play feature and the high bandwidth (12 Mbps) of USB specification.
- Offers the easiest IR wireless data access to the desktop computers.
- Does not occupy PC's COM or Parallel port and has no complicated port and resource setting and conflict, such as I/O address, IRQ / DMA numbers.
- Fully compliant to USB specification 3.0 and IrDA specification 1.4
- Obtain power from USB port. No external power supply required.
- Very compact size.
- Work easily with the link application software built into Windows 98SE, ME, 2000, XP [32 & 64 Bit], Win Vista, Windows 7/8/8.1&10 and Windows Server 2003 [32 & 64 Bit], with **WHQL Certified**.
- Also supports Win CE 4.2 & 5.0 (USB host), Linux and Mac 10.2 (Power PC only).



All trademarks, logos, organization & company names and product model names are the properties of the respective owners.

Model #ACT-IR2002UL

The only IrDA[®] adapter supplier that has test tools to help your system to be IrDA[®] compliant !



ACTISYS
The Infra-Red Wireless Expert



Specifications

ACT-IR2002UL FIR-USB Adapter

● **Compatibility:**

Fully compliant to USB specification 3.0 and IrDA[®] specification 1.4

● **Communication speed and Distance:**

SIR (9.6, 19.2, 38.4, 57.6, 115.2 kbps) & MIR (1.152 Mbps) - 1 ~ 158 cm
FIR (4 Mbps) - 1 ~ 100 cm

● **Connection:**

Standard USB connector with 4-ft USB cable

● **Power Source:**

Obtain power from USB port. No external power supply required.

● **Power Consumption:**

Active current: Sending - 55 mA; Receiving - 24 mA; Standby current: 20 mA

● **Dimension / Weight:**

41 mm(L) X18 mm(W) X 9.4 mm(H); 1.85"(L)X0.7"(W)X0.37"(H)/ 6.2 g (0.22 oz)

● **Operating / Storage Temperature:**

0° C TO 60° C / -20° C TO 85° C

● **Programmable and Default Key Parameters:**

Extra BOFs = 00; Min. Turn-Around Time = 1.0 mS; Speed Enable = 4000000;
Infrared Transceiver Type = Vishay TFD; Read Depth = 20; Read Threshold = 05;
Receive Sensitivity = Enable; Receive Window Size = 04; Receive Mode= Fast

921 Corporate Way
Fremont, CA 94539, U.S.A.
Tel: +1-510-490-8024
Fax: +1-510-623-7268
Internet: irda-info@actisys.com
Web Site: <http://www.actisys.com>

All trademarks, logos, organization & company names and product model names are the properties of the respective owners.